



WE TAKE BUILDING
AUTOMATION PERSONALLY

en

MANUAL

INPUTS AND OUTPUTS SPECIFICATIONS



THANK YOU FOR CHOOSING REGIN!

Ever since Regin was established in 1947, we have developed and marketed products and systems that create good levels of indoor comfort. Today, we are an important player with one of the market's broadest ranges for building automation.

Our goal is to make real estates in the world more energy efficient. Regin is an international group and our products sells in over 90 countries. Thanks to our global presence with strong local representation, we are well aware of the requirements of the market, as well as of how our products and systems function under the most variable conditions. Every year, Regin makes substantial investments in the development of our systems and HVAC-products.

DISCLAIMER

The information in this manual has been carefully checked and is believed to be correct. Regin makes no warranties about the contents of this manual and users are requested to report errors and discrepancies to Regin, so that corrections may be made in future editions. The information in this document is subject to change without prior notification.

Some product names mentioned in this document are used for identification purposes only and may be the registered trademarks of their respective companies.

© AB Regin. All rights reserved.

Rev. B, 2022-05-17

1	Introduction.....	5
1.1	About this manual.....	5
2	Inputs.....	6
2.1	Analog inputs	6
2.1.1	AIa.....	6
2.1.2	AIb.....	6
2.1.3	AIc.....	6
2.2	Digital inputs.....	7
2.2.1	DIa.....	7
2.2.2	DIb	7
2.3	Condensation inputs.....	7
2.4	Universal inputs.....	7
2.4.1	UIa as AI.....	7
2.4.2	UIa as DI	8
2.4.3	UIb as AI	8
2.4.4	UIb as DI.....	8
2.4.5	UIc as AI.....	9
2.4.6	UIc as DI	9
2.4.7	UId as AI	9
2.4.8	UId as DI.....	9
3	Outputs.....	10
3.1	Analogue outputs.....	10
3.1.1	AOa.....	10
3.1.2	AOb.....	10
3.1.3	AOc.....	10
3.2	Digital outputs.....	11
3.2.1	DOa.....	11
3.2.2	DOb.....	11
3.2.3	DOc.....	11
3.2.4	DOd.....	11
3.3	Universal outputs.....	11
3.3.1	UOa as AO	11
3.3.2	UOa as DO	12
3.3.3	UOb as AO.....	12
3.3.4	UOb as DO.....	12

I Introduction

I.1 About this manual

This hardware manual describes the different types of inputs and outputs that are available in Regin's controllers and regulators, e.g. Regio Ardo, EXOcompact Eedo and Add:io.

Connection diagrams and other technical details can be found in each product's manual.

2 Inputs

2.1 Analog inputs

2.1.1 Ala

AI type *a* can be configured according to the following modes :

- ✓ 0...10 V
- ✓ 0...200 mV
0(4)...20 mA (with external 10 Ω shunt)
- ✓ 800 - 1600 Ω
PT1000 (-50...+150 °C)
Ni1000 LG (-40...+120 °C)
Ni1000 DIN (-40...+105 °C)
Digital open/close (slow)
- ✓ 0 - 4000 Ω
PT1000 extended (-60...+600 °C)
Ni1000 LG extended (-50...+250 °C)
Ni1000 DIN extended (-40...+250 °C)

The technical data are as follows:

Measurement current (resistance modes)	770 uA
Input resistance (voltage modes)	10 MΩ
ADC resolution	12 bit
PT1000/Ni1000 accuracy (excluding sensor)	± 0.4 K
Voltage 0...10 V accuracy (% of full scale)	± 0.15 %
Voltage 0...200 mV accuracy (% of full scale)	± 0.15 %

2.1.2 Alb

AI type *b* can be configured according to the following mode:

- ✓ 0...10 V

The technical data are as follows:

Input resistance	98 kΩ
ADC resolution	12 bit
Voltage 0...10 V accuracy (% of full scale)	± 0.15 %

2.1.3 Alc

AI type *c* can be configured according to the following modes

- ✓ Pt1000 (-50...+150 °C)
- ✓ Digital open/close (slow)

The following modes might be available through the software configuration:

- ✓ 800 - 1600 Ω
- ✓ Ni1000 LG (-40...+120 °C)

- ✓ Ni1000 DIN (-40...+105 °C)

The technical data are as follows:

Measurement current (resistance modes)	~400 uA
ADC resolution	12 bit
PT1000/Ni1000 accuracy (excluding sensor)	± 0.4 K

2.2 Digital inputs

2.2.1 DIa

DI type *a* is of sinking input type and is designed for 0/24 V signals where 24 V normally is supplied from the controllers' +C terminal.

The technical data are as follows:

Input type	Sinking (+C, Rail)
Pulse length	>4 ms (fast)

2.2.2 DIb

DI type *b* is of sourcing input type and is designed with an internal supply of the DI. The reference is the controllers' GND or G0/- terminal.

The technical data are as follows:

Input type	Sourcing (-GND)
Pulse length	>4 ms (fast)

2.3 Condensation inputs

CI type *a* is used for all products.

2.4 Universal inputs

Universal inputs on the controller can be individually configured as either analogue inputs or as digital inputs

The default configuration of a UI is as a DI.

UIb and UIc are 24 V AC/DC tolerant.

2.4.1 UIa as AI

UI type *a* in AI mode can be configured according to the following modes:

- ✓ 0...10 V
- ✓ 0...200 mV (0(4)...20 mA with external 10 Ω shunt)
- ✓ 800..1600 Ω (Pt1000, Ni1000 LG, Ni1000 DIN)
- ✓ 0..4000 Ω (Pt1000 ext, Ni1000 LG ext, Ni1000 DIN ext)

The technical data are as follows:

Measurement current (resistance modes)	medium, 500-1000 μ A
Input resistance	medium, \sim 1 M Ω
ADC resolution	12 bit

2.4.2 Ula as DI

This type of DI can be used together with transceivers of PNP type and relays with dry contact. The reference is the external current source (+C) and sensors and transmitters shall therefore be connected to +C.

The technical data are as follows:

DI input type	Sinking
Response time	Fast
Voltage	24 V (+C)
Input resistance	<ul style="list-style-type: none"> ✓ signal < 12V: medium, \sim1MΩ ✓ signal > 12V: low, < 20 kΩ
Guaranteed detect levels	<ul style="list-style-type: none"> ✓ High ('1'): > 12 V ✓ Low ('0') < 5 V
Smallest detectable pulse width	4 ms

2.4.3 U1b as AI

UI type *b* in AI mode can be configured according to the following modes:

- ✓ Pt1000 (0...+100 °C)

The technical data are as follows:

Measurement current (resistance modes)	low, < 500 μ A
Input resistance	<ul style="list-style-type: none"> ✓ signal < 12V: high, > 10 MΩ ✓ signal > 12V: low, < 15kΩ
ADC resolution	10-12 bit

2.4.4 U1b as DI

This type of DI can be used together with transceivers of PNP type and relays with dry contact. The reference is the external current source (+C) and sensors and transmitters shall therefore be connected to +C. The smallest detectable pulse is 20 ms.

The technical data are as follows:

DI input type	Sinking
Response time	Slow
Voltage	24 V (+C)
Input resistance	<ul style="list-style-type: none"> ✓ signal < 2V: high, >10 MΩ ✓ signal > 2V: low, < 20 kΩ

2.4.5 U_{lc} as AI

UI type *c* in AI mode can be configured according to the following modes:

- ✓ 0...10 V
- ✓ 800..1600 Ω (Pt1000, Ni1000 LG, Ni1000 DIN)
- ✓ 0..4000 Ω (Pt1000 ext, Ni1000 LG ext, Ni1000 DIN ext)

The technical data are as follows:

Measurement current (resistance modes)	low, < 500 μA
Input resistance	1 MΩ
ADC resolution	12 bit

2.4.6 U_{lc} as DI

This type of DI can be used together with transceivers of NPN type and relays with dry contact. It is of sourcing input type and is designed with an internal supply of the DI. The reference is the controllers' GND.

The technical data are as follows:

DI input type	Sourcing (-GND)
Response time	Fast
Voltage, open input	6.5 V
Guaranteed detect levels	
<ul style="list-style-type: none"> ✓ Open ('0') ✓ Closed ('1') 	<ul style="list-style-type: none"> ✓ > 4V ✓ < 2 V
Smallest detectable pulse width	4 ms

2.4.7 U_{ld} as AI

UI type *d* in AI mode can be configured according to the following modes:

- ✓ 0...10 V
- ✓ 0...20 mA
- ✓ 800..1600 Ω (Pt1000, Ni1000 LG, Ni1000 DIN)
- ✓ 0..4000 Ω (Pt1000 ext, Ni1000 LG ext, Ni1000 DIN ext)

The technical data are as follows:

Measurement current (resistance modes)	low, < 500 μA
Input resistance	1 MΩ
ADC resolution	12 bit

2.4.8 U_{ld} as DI

UI type *d* as DI has the same specifications as UI type *c* as DI.

3 Outputs

3.1 Analogue outputs

3.1.1 AOa

AO type *a* can be configured according to the following mode:

- ✓ 0...10 V

The technical data are as follows:

Output resistance	< 0.5 Ω
Resolution	12 bit
D/A generation type	PWM
Output short tolerant	Yes
24 V tolerant	No
Max load	5mA

3.1.2 AO_b

AO type *b* can be configured according to the following modes:

- ✓ 0...10 V
- ✓ 0...20 mA

The technical data are as follows:

Output resistance	3 Ω
Resolution	12 bit
D/A generation type	DAC
Output short tolerant	Yes
24 V tolerant	No
Max load	1mA

3.1.3 AO_c

AO type *c* can be configured according to the following mode:

- ✓ PWM (0...100 %)

The technical data are as follows:

Output resistance	< 6 Ω
Resolution	≥ 10 bit
D/A generation type	PWM
Output short tolerant	Yes
24 V tolerant	No
Max load	10mA

3.2 Digital outputs

3.2.1 DOa

DO type *a* is a 24V DC sourcing type.

The technical data are as follows:

Output type	Sourcing
Voltage	24 V DC
Max current load	See the product manual



Note! DO as type *a* is only used in older products at Regin.

3.2.2 DOb

DO type *b* is a 24V AC/DC sinking MOSFET type.

The technical data are as follows:

Output type	Sinking MOSFET
Voltage	24 V AC/DC
Max current load	See the product manual

3.2.3 DOc

The technical data are as follows:

Output type	Relay
Voltage	230 V AC
Max current load	See the product manual

3.2.4 DOd

The technical data are as follows:

Output type	Triac
Voltage	230 V AC
Max current load	See the product manual

3.3 Universal outputs

Universal outputs on the controller can be individually configured as either analogue outputs, using any of the analogue outputs, or digital outputs.

The default configuration of a UO is as a DO.

3.3.1 UOa as AO

UO as type *a* configured as AO can be configured according to the following mode:

Outputs

✓ 0...10 V

The technical data are as follows:

Output resistance	Max 1 Ω
Resolution	\geq 10 bit
D/A generation type	PWM
Output short tolerant	Yes
24 V tolerant	Yes
Sinking capacity	No

3.3.2 UOa as DO

The technical data are as follows:

Output type	Sinking MOSFET
Voltage	24 V AC/DC
Output resistance	100 m Ω
Over-current protected	No
Over-temperature protected	No

3.3.3 UOb as AO

UO as type *b* configured as AO can be configured according to the following mode:

✓ 0...10 V

The technical data are as follows:

Output resistance	Max 3 Ω
Resolution	12 bit
D/A generation type	PWM
Output short tolerant	Yes
24 V tolerant	Yes
Sinking capacity	Yes

3.3.4 UOb as DO

The technical data are as follows:

Output type	Sinking MOSFET
Voltage	24 V AC/DC
Output resistance	Max 200 m Ω
Over-current protected	Yes
Over-temperature protected	Yes



HEAD OFFICE AB Regin, Box 116, SE-428 22 Källered • Visiting address: Bangårdsvägen 35, SE-428 36 Källered
Phone: +46 (0)31 720 02 00 • Fax: +46 (0)31 720 02 50 • info@regincontrols.com • www.regincontrols.com