



ROOM THERMOSTATS FOR FAN COIL WITH TWO 0-10 V OUTPUTS FOR 4-PIPE SYSTEM AND HEATING RELAY OUTPUT WITH ECONOMY FUNCTION FUNCTION

DB-TA-3A8..A

Temperature control in heating, ventilation, refrigeration and air conditioning for tipically 4-pipe fan coil systems with proportional valves.

- 1 heating relay output
- 2 proportional outputs 0...10 Vdc with dead zone
- manual selection of On/Off, 3 fan speeds
- economy function

The thermostat is provided with a LCD display and keys +/- for parameters setting like the range, the neutral zone, proportional

heating and cooling bands and economy mode. When the thermostat is on the fan is on at the speed selected manually and the proportional outputs are set according to parameters setting. The relay is activated if heating function is required when the maximum heating voltage output has been reached but not the temperature required.

In addition an economy function is available with a remote contact. When the contact is closed the thermostat works with an economy mode.

ТҮРЕ	ON/OFF	3-SPEED	DEAD ZONE K
DB-TA-3A8-13A	•	•	14
DB-TA-3A8-10A	•		14
DB-TA-3A8-00A			14

TECHNICAL DATA

Power supply:	24 Vac ± 10%, 50/60 Hz		
Input:	external contact for economy function		
Outputs:	valves: 2 0-10 V outputs ($R_1 > 10$ kOhm)		
	1 relay 6 A 230 Vac		
	speeds: 6 A 24/230 Vac ±10%, 50/60 Hz		
Power cons.:	1 W		
Sensor:	NTC 10K		
Setpoint:	+5+30 ℃		
Differential:	0.4 K (relay)		
Prop. band:	± 0,5± 2,5 K		
Economy:	adjustable range between 0+5 °C		
Display:	resolution 0.1 °C		
Working:	0+40 °C		
	1090% r.h. (without condensing)		
Storage:	-20+70 °C		
	< 95 % r.h.		
Housing:	ABS fireproof according to UL94 V-0 color (RAL		
	9010)		
Protection class:	IP30, class II		
Size:	144 x 82 x 34 mm		
Weight:	220 g		

Logic of proportional outputs



ZN	neutral zone
PBH	proportional heating band
PBC	proportional cooling band

WIRING DIAGRAM



ECONOMY FUNCTION contact closed: economy function selected ECONOMY FUNCTION contact open: economy function not selected

(*) only for models DB-TA-3A8-13A, DB-TA-3A8-10A

(**) only for model DB-TA-3A8-13A

Tset centered in dead zone

